

PIX DIGITAL TENSION METER

STANDARDS: THE DIGITAL TENSION METER IS USED TO CHECK THE TENSION OF DRIVE BELTS BY MEANS OF FREQUENCY MEASUREMENT.



Range of measurement:	10-600Hz
Measuring precision:	10-400Hz +/- 1%
	400-600Hz +/- 2%
	+/- 1 digit
Measuring method:	non contact acoustic with background noise suppression

Voltage supply:	2*1,5V Mignon (LR06) AA
Power consumption:	< 25 mA
Display:	LCD 2 lines of 8 characters
Working temperature:	0 to +50° C
Storage temperature:	-20 to +60°C